




FingerTec Smart Lock DL-30B is a smart mechanical door lock system designed to fit doors built for houses, restricted compounds or even individual rooms. With DL-30B in place, imagine the amount of security and convenience that could possibly come along without the use of conventional keys and door knobs.

Although it comes with a latch which is similar to other standard door knobs, DL-30B stands out by featuring an interchangeable handle thus making it suitable for both left-open or right-open door. Even better, DL-30B optimal power usage allows it to be used over 6000 times thus providing a cost effective security access point.

What's more, DL-30B's Bluetooth connectivity works best when combined with i-TimeTec App and i-Neighbour App as it eases door unlocking and management of facility booking within a neighbourhood respectively. As for safety issues, fret not as DL-30B comes with the option to set 3 different User Group Types: Admins, Regular Users or Temporary Users for additional precaution. Save valuable resources and heighten security at the same time by implementing DL-30B.





**Optimal Battery Life** Only 4 AA alkaline batteries are required to operate over 6000 accesses. Hence, approximately a year of use before you are faced with the low-battery warning indication.



**3 User Group Types** Gain better access control management with FingerTec Smart Lock User Group Types: Admins, Regular Users and



### **Reversible Left-Right** Open

DL-30B is designed with a sturdy bar latch alongside an interchangeable handle which allows the door to be easily customized as a left-open or right-open door.



#### **User Capacity**

Register as many users as you desire within i-TimeTec App and i-Neighbour App through a smartphone.




# **Emergency Override Key**

IIn case of an emergency like losing a smartphone, DL-30B comes with a concealed override key for accessing the door.







This particular setting caters for offices or areas with regular visitor access. Thereby, reducing instances resulting in entrances being 'bottlenecked'.



## **Downloadable App**

Android and iOS Apps for i-Neighbour and i-TimeTec are available for those who prefer to use a smartphone in terms of door access.

### **WEB LINK**



Quick Start Guide http://info.fingertec.com/DL30B-1




Installation Guide http://info.fingertec.com/DL30B-2



User Guide http://info.fingertec.com/DL30B-3

### **LAYOUT PLAN**

### Installation Diagram



SPECIFICATIONS	
MODEL	DL-30B
SURFACE FINISHING	RFID
ALGORITHM	Biobridge VX 10.0
RESOLUTION OF SCANNER (dpi)	560
PRODUCT DIMENSION (L X W X H), mm	Front panel: 69 x 35 x 155 (with handle)
	Back panel: 69 x 25 x 155 (without handle)
Thickness of door, mm	30-38 (optional), 39-46 (standard)
	47-54 (standard), 55-60 (optional)
Door latch type	Single deadbolt
Inner lock switch	Yes
STORAGE	
Password	100
Card	100
Bluetooth	Unlimited users for i-TimeTec App & i-Neighbour App
BLUETOOTH VERIFICATION	
Communication	Bluetooth 4.0
OPERATING ENVIRONMENT	
Voice guidance	Yes
Temperature (°C)	- 20 to – 55
Humidity (%)	20 ~ 80
Power input	4 x1.5v AA battery for 6000 operations
Power consumption – static (µA)	<35
Power consumption – activity (mA)	< 135
Power consumption – driving (mA)	< 200
Antistatic voltage (V)	> 1500
Low battery warning voltage (V)	< 4.5
BACKUP UNLOCK MECHANISM	Battery & mechanical key
MOBILE OS	Android 4.0.2 and above, iOS 8.0 and above
APP LANGUAGE	Arabic, Chinese Simplified and Traditional, English, Hindi, Indonesian, Malay, Nepali, Spanish, Thai, Turkish, Vietnamese.  Other languages are available upon request.

 $\textbf{NOTE:} Specifications \ are \ subject \ to \ change. \ \ \textit{Check http://product.fingertec.com} \ for \ latest \ product \ information.$ 



#### Packaging

Dimension (mm) :298 (L) x 123 (W) x 222 (H)

Weight :3.15 kg







